



## Product Data Sheet

# GS615

## Shock sensor analyser EOL resistors

### Shock Sensor Analyser

The single multi count analyser has an amplitude setting which allows the installer the flexibility of adjusting the level of a single shock to give an alarm activation. The analyser also has a programmable 1-second count facility which enables the alarm to be activated after a series of small shocks are received at 1-second intervals. The counter is programmable between 1-9 counts within a fixed time period of 30 seconds. If the programmed number of small shocks is received, or if one shock larger than the setting of the potentiometer is received the alarm will activate.

### Application

Residential are typical applications for these shock sensor analysers. The gross attack setting will trigger an alarm when a shock big enough is applied to the window/door. The pulse count setting will detect an intruder gently shocking a window/door after a selected number of shocks at 1-second intervals.

### EOL Resistor

The sensor loop contains a 1K end-of-line resistor wired in series with the sensors. Should the sensor loop be cut or the 1K end-of-line resistor be shortcircuited, the alarm will be activated.



### Standard Features

- Sensitivity setting
- Programmable pulse count, 1-9
- LED indication
- On-board voltage regulation
- EOL resistor
- Manual or automatic reset

# GS615

Shock sensor analyser EOL resistors

## Specifications

Power supply	10 to 15 VDC
Current consumption	
Quiescent	10 mA
Alarm	50 mA
Operating temperature	-40 to +50°C
Alarm contact rating	1 A - 12 VDC
Tamper detection	yes

## Ordering Information

Part No.	Description
GS615	Shock sensor analyser with EOL resistors and manual reset option
GS615A	Shock sensor analyser, NFa2P
GS614	Shock sensor analyser

