



CODE: **AWT042H** v.1.0/I
 NAME: **Transformer TOR100VA /24V/27V/33V
 DS-1602ZJ PTZ / Hikvision**

EN



DESCRIPTION

The transformer is designed to supply pan-tilt-zoom (PTZ) cameras. It is equipped with an adapter (sheet) mounted directly to the DS-1602ZJ-Box mount bracket by Hikvision.

Caution!

The transformer is fitted with three taps:

U1=24VAC

U2=27VAC

U3=33VAC

Before connecting the camera, check the manual to determine what voltage is required for the proper operation (Usually 24V AC). Only one tap should be used (see the diagram below).

TECHNICAL SPECIFICATION

Input voltage	230V AC / 50Hz
Power	100VA
Voltage and current output	24V/4,17A or 27V/3,7A or 33V/3,0A
Protection	fuse T10A in lead circuit
Thermal protection	fuse 130°C - non resettable (fuse in transformers winding)
Dimensions	W=154mm, H=214mm, D=64
Weight net/gross	1,88/2,00[Kg]
Wires length:	
Primary winding L1	120mm ±10mm
Secondary winding L2	170mm ±10mm
The equipment	mounting screws 4 pcs.
Declarations, warranty	CE, 2 year from the production date
Operating conditions	2nd environmental class, -10°C÷ 40°C, Ta 40B

ELECTRICAL DIAGRAM

