

KFP-AFR-FB2-xx

Addressable Fire Panel Repeater with Fire Brigade controls

Overview

The KFP-A Series life safety control systems are bringing the speed and functionality of high-end intelligent processing to small to mid-sized addressable applications. They feature an attractive contemporary design that fits with any decor. Special plastics allows for painting in any color and the easy to remove electronics will support in this matter. The gently lined door with the intuitive blue inset user interface and EN54 compliant graphical LCD offers a distinctive flair. The main controls are clearly, but discreetly highlighted with the focus on the central located Jog Dial. With the addressable detection and a full line of easily configured option cards and modules, USB and Ethernet® connectivity, these quick-to-configure systems offer versatility that benefits building owners and life safety system installers alike.

The Panel

The fire panel repeaters, with user interface with fire brigade and fire protection controls, supplied in local language come with a 2010-2-NB network board already fitted. Except for having no addressable loops and corresponding programmable outputs, the setup is similar as a normal fire panel. It has its own power supply, 2 conventional relay outputs and 2 supervised outputs, working in pair and dedicated to common fire and fault conditions, as well as 2 user configurable inputs for monitoring and control are available.

Options

The repeaters use a node on the network, similar like a normal panel with a maximum of 32 nodes / 32 loops network of fire panels and fire panel repeaters (including conventional fire panels and fire panel repeaters up to a maximum of 64 conventional zones). Last but not least, in case separate zone indications are required, a 20 or 40 zone fire/fault LED indicator board can be mounted in the panel or repeater with ample space for text.

Approvals & Compliance

- CE / CPD / EN54-2 / EN54-4 / EN54-21 • NEN2535 / NBNS21-100 compliant
- BS5839-1 compliant
- VdS and LPCB certified
- WEEE / RoHS compliant



Standard Features

- Local or global repeater with Fire Brigade and Fire Protection controls with or without global control functionality
- Up to 40 LED Zone indicators for Fire and Fault with ample text space
- Auto configuration, setup wizards and default EN54 setup modes
- Ethernet port with TCP/IP for remote diagnostics, maintenance and programming
- EN54 compliant graphical LCD with icons and up to 256 zones
- Jog Dial with 4 soft buttons for simple and intuitive user control
- Aesthetic pleasing design with special paintable synthetic door
- Easy removable door and chassis for quick and clean installation
- All pluggable connectors
- 3 USB ports with memory stick support and RS232 for printer support
- Email notification for events directly from the panel (4 user accounts)
- Auxiliary 24VDC supply output with reset support
- 3 operator level menu structure (20 usernames and passwords)
- History log memory for 9999 events
- Up to 72 hours standby time and 30 minutes alarm
- Comes standard fitted with network board

KFP-AFR-FB2-xx

Addressable Fire Panel Repeater with Fire Brigade controls

Specifications

Mains supply	
Voltage	230 / 110 VAC (+10% / -15%)
Frequency	50 / 60 Hz (±5%)
Current	Nom. 0.6 / 1.3 A, Max. 1.5 / 3.15 A
Fuse rating	2 / 4 A
Cable type	3 x 1.5 mm ² (live, neutral, earth)
Batteries	
	Max. 2 x 12V/18Ah (use supplied cables)
Outputs	
General Fire + Fault supervised	2, 350mA / 19.5-28VDC (24 VDC nominal)
General Fire + Fault relay	2
Aux	1 resetable, 500mA / 19.5-28VDC (24VDC nominal)
Cable type	Recommended 2 core 1.5 mm ² twisted pair
End of Line resistor	15kohm
Inputs	
Programmable	2
Cable type	Recommended 2 core 1.5 mm ² twisted pair
End of Line resistor	15kohm
Maximum Load	150 mA
Environmental conditions	
Storage temperature	-10°C to +50 °C
Operating temperature	-5°C to +40 °C
Relative humidity	max. 95 % (non-condensing)
Mechanical	
Size (W x D x H)	449.6 x 171.2 x 550 mm
Weight	7.4 kg (without batteries)
Color	RAL7035
Cable entries (Top / Bottom / Back)	18 (20mm) / 2 (20mm) / 2 removable plates
IP rating	IP30: for indoor use only

Ordering Information

Part No.	Description
KFP-AFR-FB2-xx	Addressable Fire Panel Repeater with Fire Brigade controls
-xx	Language Codes
KFP-A-ZI-20	
KFP-A-ZI-40	
BS127N	Sealed Lead-Acid Battery - 12V 7.2Ah
BS130N	Sealed Lead-Acid Battery - 12V 12Ah
BS131N	Sealed Lead-Acid Battery - 12V 18Ah
2010-2-FTP-C30	Addressable Fire Panel Accessory - Cable FTP CAT5 - 3m
2010-2-USB-C30	Addressable Fire Panel Accessory - Cable USB A to B - 3m
2010-2-PAK-NET128	2010-2 PAK Increases the network capability to 32 nodes and 128 loops
2010-2-PAK-NET256	Network Expansion - 64 Nodes / 256 Loops for Addressable Fire Panel
2010-2-PAK-RMSDK	2010-2 PAK Enables custom event reporting and command control using the Edwards
2010-2-PAK-RMOH	2010-2 PAK Enables the Contact ID protocol over Ethernet
2010-2-PAK-RMBN	2010-2 PAK Enables the BACnet protocol over Ethernet
2010-2-PAK-RMMB	2010-2 PAK Enables the Modbus protocol over Ethernet
2010-2-PCC-CF	
2010-2SW-FS	FiRe Server for connecting FiRe mobile apps

