

2010-2-PIB-8I

Addressable Fire Panel Accessory - Peripherals Interface Board 8 Inputs

Overview

The 2010-2-PIB-8I Peripherals Interface Board is an accessory of the small to medium size intelligent addressable life safety control systems. In total there are 4 variants of this board. The 2010-2-PIB-8I is a reduced variant of the 2010-2-PIB and is perfect if your only looking for having additional supervised inputs to interface other electronic equipment on site.

Functionality

The 2010-2-PIB-8I Peripherals Interface Board provides eight inputs for compatible control panels. Inputs and outputs are supervised for short circuit and open circuit faults.

Mounting & Connections

The board can be plugged directly on the front of the main board inside the big size control panel variants on top of the new release 3 chassis. No additional wiring is required. You can use the pluggable connectors to make your connections to the field wiring. Connect an external power supply to the board directly to reduce the load of your system.



Standard Features

- 8 supervised inputs
- Pluggable connectors

2010-2-PIB-8I

Addressable Fire Panel Accessory - Peripherals Interface Board 8 Inputs

Specifications

Operating voltage	24 VDC
Current supply	
Standby	40 mA max.
Input activation	
Open circuit	>20.2 kOhm
Quiescent	15 kOhm
Activated	60.2 Ohm to 8 kOhm
Short circuit	<60.2 Ohm
End-of-line termination	
Input (typical)	EOL 15 kOhm, 1/4 W resistor
Operating environment	
Operating temperature	-5 to +40°C
Storage temperature	-20 to +50°C
Relative humidity	10 to 95% (noncondensing)
Weight	105 g
Dimensions (W × H)	105 × 192 mm
Compatibility	Release 3 hardware / firmware

Ordering Information

Part No.	Description
2010-2-PIB-8I	Addressable Fire Panel Accessory - Peripherals Interface Board 8 Inputs